



ABN 26 371 237 667

5 Hi-Tech Place Rowville Vic 3178 (P.O.Box 1047 Upwey Vic 3158)

Phone: (03) 9764 1372 Fax: (03) 9753 2072

## Anartelle Digital Timers

### **Instructions to set timer in second increments.**

To set the Timer to work in second increments it works on 24 programs rather than the standard 12. The timers can be set for 1 to 59 seconds. To do this you use the **ALARM** function.

To start press the **CLOCK** button this will return you to the main screen. Press the **PROGRAM** button then cycle through the 12 on/off programs until you get to the ALARM function.

In the **ALARM** function press week/sec button to set the number of seconds you require to turn on for ie. 15seconds.

Now press the **PROGRAM** button to select the times you want it to turn on at.

All Programs including **OFF** times are now **ON** times, so instead of getting 12 **OFF** and 12 **ON** times you now have 24 **ON** times.

Eg. For second increments 8am **ON** and 9am **OFF** will mean that the timer will turn on for the specified number of seconds at 8am and again at 9am, now that all **OFF** programs are now also **ON** programs.

This gives you 24 possible **ON** programs instead of 12 that can be used for watering, fan times, air pumps etc.